



Wire Chart for Tach Adaptor

Color	Function
Black	Ground
Red	+12V
Red/White	+5V Output *Optional
Yellow/Red	60-2 Crank Input
Gray/Red	Out 1 – Default to 4X
Gray/Black	Out 2 – Default to 12X

Be Sure to tape up any unused wires.

Wire colors and location on PCM

Year	Color and Location
2003	WT/DG C1 pin 22
2004	LB/BR C1 pin 22 (A/T)
2004	BR/LB C1 pin 22 (M/T)
2005	LB/BR C1 pin 22
2006	LB/BR C1 pin 22
2007 5.9 or 6.7	LB/BR C1 pin 22
2008 6.7	LB/BR C1 pin 22

Year of truck	Pulses Tach needs to see
1994-1997	12
1999-2001	4
2002	12
2003	58
2004	58
2005	58
2006-2007	58